# **DMX512**

# **Decoder Series**



### **Specifications**

Model: DE8000

Input: DC12-24V Max output Power: 144W(12V)/288W(24V)

Max current Load: 4A\*3CH Max 12A Signal Input: DMX512/1990

Control channels: 3CH The light gray level: 256


Protection Grade: IP20 DMX512/PWM Socket: RJ45/Screwless terminal

Gross Weight: 220g Work Temp.: -30°C~70°C


#### **Basic Features**

- Meets DMX512/1990.with RJ45 interface.
- · 256-levels brightness,full-color with driver controls.
- Can achieve asynchronous color changes effect under working with controller.
- Cooperate with control system, can realize rich change effect.
- · Setting the DMX address freely.

#### **Dimensions**




## **Component Diagram**



# **Product Operation**

Self-testing Mode:put all DIP-Switch NO.1 to NO.9 ON full channels output 3 seconds then each color gradient.




#### How to set DMX address via DIP switch:

DMX address value = the total value of (1-9) to get the place value when in "on" position otherwise will be 0.

E.g. 1: Set Initial Address to 16.



E.g. 2: Set Initial Address to 20.



004+016=20

E.g. 3: Set Initial Address to 149.




001+004+016+128=149

#### **DMX Dimming Instruction:**

Each DE8000 DMX decoder occupied 3 DMX addresses when connecting the DMX console. E.g., the defaulted initial address is 1, please find their corresponding relationships in the form.

| DMX Console | DMX Decoder            |  |
|-------------|------------------------|--|
| CH1 0-255   | CH1 PWM 0-100% (LED R) |  |
| CH2 0-255   | CH2 PWM 0-100% (LED G) |  |
| CH3 0-255   | CH3 PWM 0-100% (LED B) |  |

#### Wiring Diagram



# Suitable lamps and lanterns







Wall Washing Lamp

LED Strip

LED Hard Light Bar Geographic Light AR111

<sup>\*</sup>An amplifier is needed when more than 32 decoders are connected, signal amplification should not be more than 4 times continuously.

<sup>\*</sup>At the end of the wiring, we should connect a DMX signal finalizer ( Put ON the switch no.10 of DE8000 dial).